








HQ-F-COMPRESSION CONNECTORS

Type	CMP MC 37		EX 6-49 NT Plus		EX 6-51	
						
Item No.	57001497		57001847		57000772	
Description	F-male		F-male		F-male	
Cable type	KOAX 58 midi		KOAX 100, 110 A+		KOAX 1170 T	
Cleaving Ø	mm	5.3	6.8		6.6	
Dielectrium Ø	mm	3.7	4.6		4.8	
Stripping A	mm	6.8	6.8		6.8	
Stripping B	mm	6.8	6.8		6.8	
Stripping tool	FACW 70 uni		FACW 70 uni		FACW 70 uni	
Compression tool	VT 300		VT 300		VT 300	

Type	EX 11		EX 59 HE		EX 6-49 IECf		EX 6-49 IECm	
								
Item No.	57000768		57001071		57001616		57001615	
Description	F-male		F-male		IECf-female		IECm-female	
Cable type	KOAX 1610 T				KOAX 100,110A+		KOAX 100,110A+	
Stripping tool	FACW 70 uni		FACW 70 uni		FACW 70 uni		FACW 70 uni	
Compression tool	VT 300		CAT 59/6 EX		VT 300		VT 300	

RETURN-WAY FILTER

- SBS-65/542: Super band stop for TV reception "Internet & Phone Only"
- SHP 3-86: For blockage of the return-way or for suppression of product interferences



Type	SBS-65/542		SHP 3-86	
Item No.	57001805		57000830	
Pass band	MHz	0-65, 542-862 (return-way, K 30 - K 69)	86-862 (FM - K 69)	
Through loss	dB	0.5	< 1	
Locked frequency range	MHz	87.5-518 (FM - K 26)	0-65 (return-way)	
Rejection depth	dB	> 50	> 50	
Dimensions	mm	60 x 20 x 20	30 x 10 x 10	